PUBLIC ADDRESS / AMPLIFIERS / MONO

MAZ-6600RU

MULTI-CHANNEL AND MATRIX PUBLIC ADDRESS AMPLIFIER



RADIO SD USB

- Excellent features
- Matrix allocation of 5 input channels to 6 output zones
- Features USB/SD player with digital radio FM tuner
- Musical alert tones

+ Info:
https://fonestar.com/MAZ-6600RU

ESPECIALLY RECOMMENDED IN:



Hospitality



Education



All sectors

DESCRIPTION

6 x 100 W RMS matrix amplifier. 6 speaker zones. USB/SD/FM player.

TECHNICAL CHARACTERISTICS

FEATURES	Matrix and multi-channel amplifier. Assignment matrix from 5 input channels to 6 output zones. USB/SD player. Digital FM tuner. 6 zones with independent volume control. Phantom power supply. Musical warning tones. Warning priority. Remote control for USB/SD/FM player.
POWER	6 x 100 W RMS
RESPONSE	80-18,000 Hz ±3 dB
DISTORTION	Harmonic: < 0.5%
S/N RATIO	Microphones: > 65 dB Aux: > 75 dB
INPUTS	1 unbalanced mic., 6.3 mm jack, 4 mV RMS 2 balanced mics/lines, combo (XLR and 6.3 mm jack) 4 mV RMS / 400 mV RMS, switchable 1 DVD/CD/AUX stereo aux, 2 x RCA 220 mV RMS, 160 mV RMS, 110 mV RMS, selectable 1 stereo aux, 3.5 mm jack, 200 mV RMS
OUTPUTS	1 stereo monitor, 6.3 mm jack
CONTROLS	6 zone buttons 1 to 6 for each input channel 2 to 5 and USB/SD/FM player Channels 1 to 4: volume, bass and treble control Zones 1 to 6: volume control, monitor selector Monitor volume
PLAYER	USB/SD player and digital FM tuner with presets and auto-scan
PHANTOM	48 V in mics 2 and 3, selectable
PRIORITY	Mic. 1 through signal level or contact closure, selectable



+ Info:
https://fonestar.com/MAZ-6600RU

IMPEDANCE	6 zones: 8 Ohm and 100 and 70 V lines, screw terminals
POWER SUPPLY	230/115 V AC, 1,000 W maximum
DIMENSIONS	420 x 133 x 376 mm depth. 3 U 19" rack
WEIGHT	17.5 kg
ACCESSORIES	FM antenna Mounts for assembling in 19" rack

+ Info:
https://fonestar.com/MAZ-6600RU