

MuxLab Audio AMP over IP Extender, RX

MIP 100 MJPEG (1080p) low latency 1G

Tuotekoodi:	500755-AMP-RX
EAN:	627699837559
Valmistaja:	MuxLab
%t_warranty%:	36



MuxLab 500755-AMP-RX is a receiver allowing a one of two 2CH analog audio-in and Mic-in signals to be extended over an IP network, and up to 100m from an Ethernet Switch via Cat5e/6 cable in a point-to-point configuration. Point-to multipoint and multipoint-to-multipoint is supported by connecting several Transmitters and Receivers to the same local Ethernet network. Depending on the application one or more Transmitters (500755-AMP-TX) can communicate with (or multicast to) multiple Receivers (500755-AMP-RX).The Transmitter supports PoE (PD) if used with a PoE (PSE) Ethernet Switch.

Supports bidirectional RS232 and directional IR transmission initiated via an IP network or via pass through for remote control of end devices.

- Extend 2CH audio signals up to 100m over Cat5e/6 cable
- Supports point-to-point, point-to-multipoint and multipoint-to-multipoint applications
- Supports 100's of Transceivers depending on network bandwidth
- Supports RS232 and IR transmission for remote control
- 2CH Analog Audio In/Out & Digital Audio Out
- PoE powered