

MICROPHONE / WIRELESS MICROPHONES / ACCESSORIES

FCM-970-MC3

FLESH-COLOURED HEAD-WORN CONDENSER MICROPHONE

**PHANTOM**
1-10 V DC

- ✓ High sensitivity, omnidirectional
- ✓ Mini XLR 3-pin connector for mod. SONAIR-PRO
- ✓ Elegant design
- ✓ Flesh colour
- ✓ Adjustable



+ Info:
<https://fonestar.com/FCM-970-MC3>

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Flesh coloured head-worn omnidirectional electret condenser microphone. Mini XLR 3 pins for mod. SONAIR-PRO

TECHNICAL CHARACTERISTICS

FEATURES	Miniature omnidirectional electret condenser capsule. For wireless microphones or electret condenser microphone inputs. Flesh colour. Adjustable.
RESPONSE	20-20,000 Hz
SENSITIVITY	-42 dB $\pm$ 2 dB (V/Pa)
MAXIMUM SOUND PRESSURE LEVEL	125 dB
IMPEDANCE	1,000 Ohm
POWER SUPPLY	1 to 10 V DC
CABLE	1.2 m
MATERIAL	Steel
CONNECTOR	3-pin female Mini XLR connector Pin 1: ground (GND). Pin 3: signal
COMPATIBILITY	FCM-970-TS, Jack 3'5 mm mono for mods. MSHT-45P/MSH-135 FCM-970-TSM, 3'5mm mono jack with male thread for mods. SONAIR FCM-970-MC3, mini XLR 3-pin for mods. SONAIR-PRO, AKG and Gemini FCM-970-MC4, mini XLR 4-pin for mod. MSH-236 FCM-970-MC4S, mini XLR 4-pin for mods. Shure and JTS
ACCESSORIES	Wind-shield foam



+ Info:

<https://fonestar.com/FCM-970-MC3>